



Carbon Monoxide Detector CEM CO-181 This CO Detector detects the presence of carbon monoxide (CO) and measures the concentration between 1-1000 parts per million (ppm) The meter indicates the presence of CO by a reading on the LCD and a beeper tone.

- Digital LCD Display
- Auto Zero
- Auto / Manual Zero
- Memory for 10 Complete data sets
- Record Mode
- LED Light audible alarm
- High Accuracy, quick response
- Pocket size and easy to use
- Fast Sampling
- Max Hold
- Auto Power Off
- Above 200ppm, the beeper sounds continuously.

Operating Temperature	0°C to 50°C
Storage Temperature	-30°C to 60°C
Operating Humidity	0-90% RH (Non condensing)
Measurement Range	0-1000PPM
Measurement Resolution	1PPM
Accuracy	±5% or ±10PPM
Warm up Period	Less than 2 seconds
Battery	9V NEDA 1604 or Equivalent
Auto Power Off	After 15 minutes
Sensor Type	Stabilised electrochemical Gas Specific (CO)
Typical sensor life	3 years